



Netcomm V100 VoIP Adaptor Configuration Instructions

Version 1.0

A. Physical Connection

1. Connect the device as illustrated



B. VoIP Settings

1. Insert the CD-ROM provided in your package
2. The following screen will appear automatically



3. Click the “Install the V100 Utility Software” button and follow the onscreen prompts to install the utility.
4. Upon the completion of installing the configuration utility, you will find the corresponding icons on your Windows desktop.



(Shortcut on your Windows desktop)

- Once the configuration utility has been installed, clicking on the SIP tab brings up the following screen. Input the information as illustrated

NetComm V100 PCTool

Status | Connection Mode | **SIP** | Telephone Book | Tool

Local | CallForward | STUN

Host

Max Digits (1-24) : 24

Port No. : 5060

MaxRings : 15

Use Proxy : Yes

Phone Configuration

User Name : Extension #

Display Name : Extension #

Codec : G729

DTMF : RFC 2833

Proxy and Registrar

Proxy / Registrar Info : sip2.bbpglobal.com Port No. : 5060

Domain Info : sip2.bbpglobal.com

Auth. User Name : Extension #

Auth. Password : Password

Expire : 300

Qvalue (0-1.0) : 0.8

Apply Refresh Close

- Click "Apply" to complete